



## Compatible Dimmer List



**MEGAMAN® LED Candle 5W and LED Classic 5W  
LC0305dv2, LC0305dCSv2, LG0505dv2 and  
LG0505dCSv2**

*Dimmer List 220-240V*

Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED Lamp(s) compatible*
Altenburger	EHR600W	220-240	60-600	6
Altenburger		220	60-400	6
ANAM	ASW3000-1	220-240	1000	6
Broco	F25AF	220-240	60-500	6
Bticino	CW20 802	250	400	6
Bticino	DG07074	220-240	40-900	6
Bticino	M9350S	220-240	500	6
Busch	2210	220-240	60-400	6
Busch	2210	230	60-400	6
Busch	2210-510	220-240	400	6
Busch	2250U	220-240	60-600	6
Chengli	27V500	250	500	6
Clipsal	32E2CFLDM	220-240	300	6
Clipsal	32V 500 series	220-240	500	6
Clipsal	S//E32	250	500	6
Crabtree	CRO-1W400	220-240	10-600	6
Danlers	DG04017	200-240	60-400	6
Danlers	DG04017	230	60-400	6
Danlers	DG05014	230	60-400	6
Dimmalite	EUR400	230	60-400	6
Doyle & Tratt Products	7066	220-240	40-250	6
Doyle & Tratt Products	P400	220-240	60-400	6
Drespa	814	230	60-400	6
Eljo	DG07100	220-240	60-600	6
Elko	400GLI	220-240	40-400	6
Eltako	EUD12NPN-UC	230	400	6
Eltako	EUD61NPN-UC	230	500	6



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED Lamp(s) compatible*
Era	DG07037	220-240	300	6
Everfourish	EF0700DA	220-240	50-300	6
Garieg	DG04043	220-240	200	6
GET		200-240	60-250	6
GET		200-250	60-250	6
Hamilton	L400/2	220-240	400	6
HPM	CAT1000L	220-240	400	6
HPM	CAT400L	220-240	10-400	6
iGoto	DG04041	220-240	200	6
Jung	244EX	220-240	60-400	6
Keytop	BP1000	220-240	1000	6
Legrand	ADWGL4	220-240	40-400	6
Legrand	Mosaic	220-240	60-500	6
LK	DG04052	220-240		6
Makel				6
Megaman	MB500	220-240	500	6
Merlin Gurin	MGU351118	230	400	6
MK	42804PL	230	40-250	6
MK	GX8051	220-240	40-500	6
MK	SX8051	240	40-500	6
Naitaina	DG04065	220-240	15-350	6
National	WEG57515	220-240	40-500	6
National	WNG6801	220-240	500	6
NIBO	09-013	230	60-300	6
Niko	310-016			6
Omni	WDM-502	250	500	6
POL	CAT 1593M	220-240	500	6
Relco	RM0736	220-240	60-500	6
Richmond	GRID400CFL	240	400	6
Richmond	GRID500	240	40-500	6
Schneider	LTD300	230	300	6
Schneider	SD300	220-240	300	6
Sicherung	Grundtyp H1	230	25-500	6
Siemens	Dimmer 15-500W	230	15-500	6
Simon	Simon-813	220-240	40-500	6



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED Lamp(s) compatible*
Soben	DG07079	220-240	630	6
Switchlight	SW-316	220-240	500	6
T&J	DG07046	220-240	40-630	6
T&J	P2017S	220-240	0-630	6
TCL		220-240	500	6
Theben	Dimax 532	230	500	6
Theben	Dimax 534	230	500	6
Venus	9720	220	40-900	6
Viko	90 30 48	220	600	6
Vimar	14150	230	100-500	6
Vivian	D-21102	220-240	1000	6
Waisbord			800	6

Remarks: \*The maximum number of LED lamps compatible is depend on the transformer performance.  
Copyright © MEGAMAN® 2011. All rights reserved.  
All information contained in this publication is correct at time of update and subject to change without prior notice.

All other trademarks mentioned are the property of their respective owners.



## Compatible Dimmer List

**MEGAMAN® LED Classic 5W and LED Globe 8W  
LG0408dv2, LG0708dv2 and LG0808dv2***Dimmer List 220-240V*

Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED Lamp(s) compatible*
Altenburger		220	60-400	6
Altenburger		220	60-600	6
ANAM	ASW3000-1	220-240	1000	6
Bticino	M9350S	220-240	500	6
Busch	2200	230	60-400	6
Busch	2210	230	60-400	6
Busch	2250U	230	600	6
Castel 2	130 290	230	60-300	6
Chengli	27V500	250	500	3
Clipsal	32V500 Series	230	500	6
Clipsal	S//E32	250	500	6
Contactum	P400	216-253	60-400	6
Crabtree	CRO-1W400	220-240	10-600	6
DETA	1954CH	200-250	60-400	6
Dimmalite	EUR400	230	60-400	3
Drespa	814	230	60-400	6
Eljo	DG07100	220-240	60-600	6
Elko	400GLI	220-240	40-400	6
Era	DG07037	220-240	300	6
Everflourish	EF0700DB	230	50-300	6
Everfrouish	EF0700DA	220-240	50-300	6
Finder	Multifunction dimmer	230	3-500	5
GET	GET 60-400W	220-240	60-400	6
GET		200-250	60-250	6
GET		200-240	60-250	6
Gira	03000	230	20-500	4
Hamilton	L400/2	220-240	400	6



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED lamp(s) compatible*
HPM	L400/2	220-240	400	1
HPM	CAT1000L	220-240	10-400	6
HQ	CAT400L	230	100	6
IKEA	EL-ECODIM-HQ	220-240	15-100	6
Jung	EED100PRS	220-240	60-400	6
Legrand	244EX	230	60-500	6
Legrand	744 05	220-240	40-400	6
Legrand	ADWGL4	230	60-600	2
Leviton	ADW-GL6	220	400	6
LK	BME04-2L	230	20-300	6
Makel	506DA117			6
Megaman		250	500	6
Merlin Gurin	MBL500S	230	400	6
MK	MGU351118	230	40-250	6
MK	42804PL	230	60-450	6
MK	L/N1511	240	40-500	6
Naitaina	SX8051	220-240	15-350	6
National	DG04065	220-240	500	6
National	WNG6801			2
NIBO		230	60-300	6
Niko	09-013			6
Norvika	310-016	250	30-500	3
Relco	200074	220-240	60-500	4
Richmond	RM0736	230	40-400	6
Richmond	MP500	240	400	6
Schneider	GRID400CFL	230	300	6
Schneider	LTD300	220-240	300	4
Schneider	SD300	220-240	300	6
Sicherung	SD300	230	40-400	6
Sicherung	8085	230	25-500	6
Siemens	Grundtyp H1	230	50-400	6
Simon		220-240	40~500	6
Soben	Simon-813	220	500	6
T & J	SH100-03-2	230	40-630	3
T & J	K211-M2 7H12	230	40-630	6



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED lamp(s) compatible*
T & J	P2017S	220-240	0-630	6
Venus	9720	220	40-900	6
Viko	215	220-240	600	6
Viko	90 30 48	220	600	6
Waisbord			800	6
Wonpro	WF Series	250	500	6
Wuyun	W13-C142	220-240	20-400	6
Yamabishi Electric	SVD-2102	230		3

Remarks: \*The maximum number of LED lamps compatible is depend on the transformer performance.  
Copyright © MEGAMAN® 2011. All rights reserved.  
All information contained in this publication is correct at time of update and subject to change without prior notice.

All other trademarks mentioned are the property of their respective owners.



## Compatible Dimmer List

**MEGAMAN® LED PAR16 Reflector 8W  
LR1108d-50H35D***Dimmer List 220-240V*

Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED Lamp(s) compatible*
Altenburger	EHR600W	220-240	60-600	6
Broco	F25AF	220-240	60-500	6
Bticino	DG07074	220-240	40-900	6
Bticino Gewiss	CW20 802	250	400	6
Busch	2210-510	220-240	400	6
Clipsal	32V 500 series	220-240	500	6
Crabtree	CRO-1W400	220-240	10-600	6
Danlers	DG04017	220-240	60-400	6
Danlers	DG05014	230	60-400	6
Dimcontrol	CFL-100	230	1000	6
Doyle & Tratt Products	7066	220-240	40-250	6
Doyle & Tratt Products	P400	220-240	60-400	6
Elko	400GLI	220-240	40-400	6
Eltako	EUD12NPN-UC	230	400	6
Eltako	EUD61NPN-UC	230	500	6
Era	DG07037	220-240	300	6
Everfrouish	EF0700DA	220-240	50-300	6
Garieg	DG04043	220-240	200	6
GET	GET 60-400W	220-240	60-400	6
Gira	03000	230	20-500	6
Gira	16200/I00	230		6
Hamilton	L400/2	220-240	400	6
HPM	CAT1000L	220-240	400	6
HPM	CAT400L	220-240	10-400	6
iGoto	DG04041	220-240	200	6
Jung	244EX	220-240	60-400	6



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED lamp(s) compatible*
Keytop	BP1000	220-240	1000	6
Legrand	670 85	230	40-400	6
Legrand	ADWGL4	220-240	40-400	6
Legrand	Mosaic	220-240	60-500	6
Magic	RT34 Magic			6
MK	42804PL	230	40-250	6
MK	GX8051	220-240	40-500	6
MK	L/N1511	230	60-450	2
MK	SX8051			6
National	WNG6801	220-240	500	6
Norvika	200074			6
POL	CAT 1593M	220-240	500	6
Richmond	MP500	230	40-400	6
Richmond	GRID400CFL	240	400	6
Richmond	GRID500	240	40-500	6
Schneider	SD300	220-240	300	6
Siemens	Dimmer 15-500W	230	15-500	6
Simon	Simon-813	220-240	40-500	6
Soben	DG07079	220-240	630	6
Stromfors		220-240	40-300	6
T & J	DG07046	220-240	40-630	6
T & J	P2017S	220-240	0-630	6
theben	Dimax 534	230	500	6
Viko		220-240	600	6
Vivian	D-21102	220-240	1000	6
Wintop	13112	220-240	40-500	6
Wuyun	W13-C142	220-240	20-400	6
Yamabishi Electric	SVD-2102			6

Remarks: \*The maximum number of LED lamps compatible is depend on the transformer performance.  
 Copyright © MEGAMAN® 2011. All rights reserved.  
 All information contained in this publication is correct at time of update and subject to change without prior notice.

All other trademarks mentioned are the property of their respective owners.



## Compatible Dimmer List



### MEGAMAN® LED PAR38 Reflector 20W LR0920d-25M25D

*Dimmer List 220-240V*

Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED Lamp(s) compatible*
Altenburger	EHR600W	220-240	60-600	5
Altenburger		220	60-400	5
ANAM	ASW3000-1	220-240	1000	5
Broco	F25AF	220-240	60-500	5
Bticino	DG07074	220-240	40-900	2
Busch	2210	230	60-400	5
Busch	2210	220-240	60-400	5
Busch	2210-510	220-240	400	5
Busch	2250U	220-240	60-600	1
Chengli	27V500	250	500	5
Clipsal	32E2CFLDM	220-240	300	5
Clipsal	32V 500 series	220-240	500	4
Clipsal	S//E32	250	500	5
Crabtree	CRO-1W400	220-240	10-600	5
Danlers	DG04017	230	60-400	5
Danlers	DG04017	200-240	60-400	5
Danlers	DG05014	230	60-400	5
Dimmalite	EUR400	230	60-400	5
Doyle & Tratt Products	7066	220-240	40-250	5
Doyle & Tratt Products	P400	220-240	60-400	5
Drespa	814	230	60-400	5
Eljo	DG07100	220-240	60-600	5
Elko	400GLI	220-240	40-400	5
Eltako	EUD12NPN-UC	230	400	5
Eltako	EUD61NPN-UC	230	500	5
Everfrouish	EF0700DA	220-240	50-300	5



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED lamp(s) compatible*
Garieg	DG04043	220-240	200	5
GET		220-240	60-250	1
GET		200-250	60-250	5
Hamilton	L400/2	220-240	400	5
HPM	CAT1000L	220-240	400	5
HPM	CAT400L	220-240	10-400	5
iGoto	DG04041	220-240	200	5
Jung	244EX	220-240	60-400	1
Keytop	BP1000	220-240	1000	5
Legrand	ADWGL4	220-240	40-400	5
Legrand	Haut 100-1000VA	250	100-1000	5
Legrand	Mosaic	220-240	60-500	5
LK	506DA116	230	20-300	3
Megaman	MB500	220-240	500	5
Merlin Gurin	MGU351118	230	400	5
MK	GX8051	220-240	40-500	5
MK	SX8051	240	40-500	5
Naitaina	DG04065	220-240	15-350	5
National	WEG57515	220-240	40-500	1
National	WNG6801	220-240	500	5
NIBO	09-013	230	60-300	2
Niko	310-016			5
Nortronic	ATD500 GLE	220-240	50-500	5
Omni	WDM-502	250	500	5
Relco	RM0736	220-240	60-500	2
Richmond	GRID400CFL	240	400	5
Richmond	GRID500	240	40-500	5
Richmond	GRID700	240	75-700	5
Schneider	SD300	220-240	300	2
Sicherung	Grundtyp H1	230	25-500	5
Siemens	Dimmer 15-500W	230	15-500	5
Simon	Simon-813	220-240	40-500	5
Soben	DG07079	220-240	630	5
Switchlight	SW-316	220-240	500	2



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Max. number of LED lamp(s) compatible*
T & J	P2017S	220-240	0-630	1
Theben	Dimax 532	230	500	5
Venus	9720	220	40-900	2
Viko	90 30 48	220	600	5
Vimar	14150	230	100-500	5
Vivian	D-21102	220-240	1000	2
Waisbord			800	5

Remarks: \*The maximum number of LED lamps compatible is depend on the transformer performance.  
Copyright © MEGAMAN® 2011. All rights reserved.  
All information contained in this publication is correct at time of update and subject to change without prior notice.

All other trademarks mentioned are the property of their respective owners.